



— DES-1026G

»»»  
The DES-1026G switch provides 24 auto-sensing 10/100Mbps ports and 2 10/100/1000Mbps copper Gigabit ports in a rack-mount box. The switch allows mix and match of Ethernet, Fast Ethernet and Gigabit in full- and half-duplex modes.

## 24-port 10/100Mbps Switch With 2 Built-in Copper Gigabit Connections

*The DES-1026G is an unmanaged 10/100Mbps switch designed to enhance workgroup performance while providing a high level of flexibility. It provides 24 10/100Mbps ports for workstation connection, plus 2 copper Gigabit ports for server deployment, allowing a workgroup to multiply bandwidths, boost response time and satisfy heavy load demands.*

### **24 10/100Mbps Ports for Workstation Connection**

The switch comes with 24 10/100Mbps ports, allowing a small workgroup to flexibly integrate to Ethernet and Fast Ethernet. These intelligent ports detect the network speed and auto-negotiate between 10BASE-TX and 10BASE-T, as well as between full and half-duplex.

### **2 Copper Gigabit Ports for Server Connection**

2 copper Gigabit ports provide an inexpensive alternative solution to fiber-optic. Using your existing low-cost Cat. 5 copper twisted-pair wires as the transmission media, these ports allow you to instantly upgrade your servers to Gigabit capability without requiring you to install new, expensive fiber cables. Both ports support 10/100/1000Mbps network speed auto-sensing and full/half duplex auto-negotiation.

### **Flow Control for Secure Transmission**

All ports support flow control. This function minimizes dropped packets by sending out collision signals when the port's receiving buffer is full.

### **Auto-negotiation of MDI/MDIX Cross Over**

All ports support auto-negotiation of MDI/MDIX cross over. This eliminates the need for cross over cables or uplink ports. Any port can simply plug to a workstation, a server, a hub or a switch, using the usual straight-through twisted-pair cable.

### **Plug-and-Play**

With 26 plug-and-play ports, the switch is a perfect choice for workgroups to upgrade performance in a client/server environment. The ports can be connected to workstations and servers in full-duplex, or hubs in half-duplex.

---

### **Features**

- 24 10/100Mbps Fast Ethernet ports
- 2 10/100/1000Mbps copper Gigabit ports
- Auto MDI/MDIX for each port
- Full/half-duplex support for each port
- Flow control for protection against data loss for each port
- Auto-learning of network configuration
- Secure store-and-forward switching scheme
- Per-port auto-correction of reverse twisted-pair polarity
- Standard 19-inch rack-mount size

# DES-1026G

## Technical Specifications

10/100Mbps Unmanaged Switch With Gigabit Connections

### General

#### Standards

- IEEE 802.3 10BASE-T Ethernet (twisted-pair copper)
- IEEE 802.3u 100BASE-TX Fast Ethernet (twisted-pair copper)
- IEEE 802.3ab 1000BASE-T Gigabit Ethernet (twisted-pair copper)
- ANSI/IEEE 802.3 NWay auto-negotiation
- IEEE 802.3x Flow Control

#### Protocol

CSMA/CD

#### Data Transfer Rates

- Ethernet:
  - 10Mbps (half-duplex)
  - 20Mbps (full-duplex)
- Fast Ethernet:
  - 100Mbps (half-duplex)
  - 200Mbps (full-duplex)
- Gigabit Ethernet:
  - 2000Mbps (full duplex)

#### Topology

Star

#### Network Cables

- 10BASE-T:
  - UTP Cat. 3, 4, 5 (100 m max.)
  - EIA/TIA-586 100-ohm STP (100 m max.)
- 100BASE-TX, 1000BASE-T:
  - UTP Cat. 5, Cat. 5e (100 m max.)
  - EIA/TIA-568 100-ohm STP (100 m max.)

#### Number of Ports

- 10/100Mbps port x 24
- 10/100/1000Mbps port x 2

#### Media Interface Exchange

Auto MDI/MDI-X for each port

#### Twisted-pair Rx Reverse Polarity

Auto-correction for each port

#### Diagnostic LEDs

Per device:

- Power

Per port:

- Link/Activity
- 100Mbps speed (10/100Mbps ports)
- 100Mbps, 1000Mbps speeds (10/100/1000Mbps ports)

### Performance

#### Transmission Method

Store-and-forward

#### Filtering Address Table

8K entries per device

#### MAC Address Learning

Automatic update

#### Packet Filtering Rates

- 10BASE-T: 14,880 pps per port (half-duplex)
- 100BASE-TX: 148,810 pps per port (half-duplex)
- Gigabit Ethernet: 1,488,100 pps per port

#### Packet Forwarding Rates

- 10BASE-T: 14,880 pps per port (half-duplex)
- 100BASE-TX: 148,810 pps per port (half-duplex)
- Gigabit Ethernet: 1,488,100 pps per port

#### RAM Buffer

512Kbytes per device

### Physical & Environmental

#### Power Supply

100 - 240 VAC, 50/60 Hz 0.3A  
Internal universal power supply

#### Power Consumption

30 watts (max.)

#### Ventilation

40 x 40 mm DC fan x 2

#### Operating Temperature

0° - 40°C (32° - 104°F)

#### Storage Temperature

-10° - 70°C (12° - 158°F)

#### Humidity

5% - 90% RH non-condensing

#### Dimensions

440 (W) x 200 (D) x 44 (H) mm (17.3 x 7.8 x 1.73 inches)  
19-inch rack-mount width, 1 U height

#### Weight

2.8 kg (6.17 lb.)

#### Emission (EMI)

- FCC Class A
- CE Class A
- VCCI Class A
- C-Tick

#### Safety

- CUL



ACN 052 202 838



LISTED  
ITE  
E141136  
66F9

### Ordering Information

#### Ethernet/Fast Ethernet Switch with Gigabit connections

**DES-1026G** 24 10/100Mbps ports  
2 10/100/1000Mbps ports

# D-Link®

Specifications subject to change without prior notice.  
D-Link is a registered trademark of D-Link Corporation/D-Link System, Inc. All other trademarks belong to their proprietors.

<b>U.S.A.</b>	TEL: 1-949-788-0805	FAX: 1-949-753-7033
<b>Canada</b>	TEL: 1-905-828-5033	FAX: 1-905-829-5095
<b>Europe</b>	TEL: 44-20-8731-5555	FAX: 44-20-8731-5511
<b>U.K.</b>	TEL: 44-20-8731-5555	FAX: 44-20-8731-5511
<b>Germany</b>	TEL: 49-61-96779900	FAX: 49-61-967799300
<b>France</b>	TEL: 33-1-30238688	FAX: 33-1-30238689
<b>Benelux</b>	TEL: 31-10-204-5740	FAX: 31-10-204-5880
<b>Italy</b>	TEL: 39-02-2900-0676	FAX: 39-02-2900-1723
<b>Iberia</b>	TEL: 34-93-4090770	FAX: 34-93-4910795
<b>Sweden</b>	TEL: 46-(0)8-564-61900	FAX: 46-(0)8-564-61901
<b>Norway</b>	TEL: 47-22-991890	FAX: 47-22-205700
<b>Denmark</b>	TEL: 45-43-969040	FAX: 45-43-424347
<b>Finland</b>	TEL: 358-9-2707-5080	FAX: 358-9-2707-5081
<b>Singapore</b>	TEL: 65-6774-6233	FAX: 65-6774-6322
<b>Australia</b>	TEL: 61-2-9417-7100	FAX: 61-2-9417-1077
<b>Japan</b>	TEL: 81-3-5434-9678	FAX: 81-3-5434-9868
<b>China</b>	TEL: 86-010-8518-2533	FAX: 86-010-8518-2250
<b>India</b>	TEL: 91-22-652-6696	FAX: 91-22-652-8914
<b>Middle East</b>	TEL: 202-6356176	FAX: 202-6356192
<b>South America</b>	TEL: 56-2-232-3185	FAX: 56-2-232-0923
<b>Brazil</b>	TEL: 55-11-3094-2910	FAX: 55-11-3094-2921
<b>South Africa</b>	TEL: 27(0)126652165	FAX: 27(0)126652186
<b>Russia</b>	TEL: 7-095-737-3389	FAX: 7-095-737-3390
<b>Taiwan</b>	TEL: 886-2-2910-2626	FAX: 886-2-2910-1515
<b>D-Link Corp.</b>	TEL: 886-2-2916-1600	FAX: 886-2-2914-6299



RECYCLABLE  
Rev. 01 (Aug. 2002)  
Printed in Taiwan